

# KODAK OMS NAVIGATOR Practice Management Software / Internet Version v5.0 System Requirements

---

OMS Navigator software strongly adheres to compliance with Microsoft Windows operating systems and hardware compatibility (HCL), which can be found at <http://www.microsoft.com/whdc/hcl/default.mspx>. Only operating systems and hardware listed below have been fully tested and certified on Kodak OMS Navigator practice management software, internet version v5.0. System Requirements are updated regularly. Before purchasing any equipment, please review the latest requirements at <http://www.kodak.com/global/en/health/dental/documentation/sysReqs/NetOMS.pdf>.

<b>Item</b>	<b>Minimum Required</b>	<b>Recommended</b>	<b>Notes</b>
<b>Computer System</b>	Intel Pentium III CPU processor or faster 1.44 floppy drive Keyboard Mouse CD-ROM Network Adapter	Intel Pentium IV 2.0 GHz CPU processor or faster	Please make sure the computer system selected is Microsoft Certified for Windows 98, Windows NT, Windows 2000, or Windows XP operating systems.
<b>Operating System</b>	Windows XP professional system Windows 2000 professional system Windows NT 4.0 workstation system Windows 98 (second edition) system	Windows XP professional system	OMS Navigator software does not support the Microsoft Windows ME operating system.  Please install your operating system on a FAT32 or NTFS file system.
<b>System Memory</b>	<u>Workstation:</u> 128MB	<u>Workstation:</u> 256MB or higher	Increasing the amount of RAM often improves performance.
<b>Hard Drive</b>	<u>Workstation:</u> 5 GB	<u>Workstation:</u> 10 GB or larger	Disk compression or other utilities should not be used.
<b>Monitor and Video Card</b>	17" monitor 1024 x 768 resolution 8MB video RAM	17" monitor or 15" flat panel LCD or larger 1024 x 768 resolution 16MB video RAM 32-bit True Color	Monitor size selection should be based upon space considerations and where the monitor will be located. A flat panel may be desirable in confined spaces.

<b>Item</b>	<b>Minimum Required</b>	<b>Recommended</b>	<b>Notes</b>
<b>Modem</b>	28.8 baud or higher speed  A modem is required to submit claims electronically.	56k U.S Robotics external modem  A modem is required to submit claims electronically.	<b>A dedicated external 56K modem is required for use with the ICOM electronic claim submission service.</b> This modem should be installed on the user's workstation and can share phone lines. An additional modem is required for each workstation <u>transmitting</u> electronic claims data.  Although you will be utilizing a DSL or Cable Internet connection to connect to the OMS Navigator software server, we strongly advise that you configure an Internet dial-up on one PC. In the event of a problem with your high-speed connection, you can utilize your dial-up connection to connect to the Internet server.
<b>Citrix Software</b>	Citrix ICA client software, version 6.20.985 or later	Citrix ICA client software, version 7.00.17534 or greater	The Citrix ICA client software must be loaded on every PC.  Please call the OMS Navigator software support department for detailed installation instructions for the Citrix ICA client software.  For optimal viewing, change your Citrix Windows system properties to use 32 bit True Color.
<b>UPS/Surge Suppressors</b>	Not required to run OMS Navigator software, but strongly recommended	UPS devices with a wattage level capable of supplying sufficient power to your system	A UPS device will supply power to your system in the event of a power failure. Kodak recommends that you work with your hardware vendor to configure a UPS solution adequate for your network.
<b>Internet Connection</b>	<u>ISDN</u> 1-3 Users = 128KB  <u>DSL (ADSL/SDSL)</u> 1-6 Users = 384KB 6-12 Users = 384-768KB  <u>Cable Internet</u> 500KB or greater. Most cable connections provide 768KB or higher speeds.  <u>T-1 (Data, not voice)</u> 1-6 Users 384K (Fractional T-1) 6-20 Users 512K or greater  <u>Hardware</u> ISDN, DSL or Cable Router.  <i>DO NOT GET A DSL OR CABLE MODEM FROM YOUR PROVIDER; make sure you order a ROUTER.</i>	SDSL or Cable Internet connection. SDSL connections tend to be more reliable than ADSL. Check with your local hardware vendor for recommendations in your area.	The quality of the Internet connection is a vital aspect of the OMS Navigator software, internet version. A poor quality connection will negatively affect your experience utilizing the application.  SDSL lines are usually available from companies such as UUnet and AT&T or local providers. ADSL lines are provided by the local telephone company.  SDSL and ADSL connections are the most widely used by our existing clients. SDSL connections are primarily used by business users while ADSL are used predominately by residential users.  A T-1 line is a highly reliable and fast connection, but due to high cost may not be a viable option for many clients.
<b>Firewall Protection</b>	Not required to run OMS Navigator software	Hardware or software firewall	It is recommended that you contact your hardware vendor to configure firewall protection appropriate to your network.

<b>Item</b>	<b>Minimum Required</b>	<b>Recommended</b>	<b>Notes</b>
<b>Scanners</b>	Required only if scanning radiographs or other images	Epson Expression 1680 professional scanner with transparency adapter	Installing two or more scanners on the same workstation is not recommended.
<b>Printers</b>	<u>Laser Printer:</u> HP LaserJet 2100 printer HP LaserJet 2200 printer HP LaserJet 4000 printer HP LaserJet 4050 printer HP LaserJet 4100 printer  <u>Label Printer:</u> Seiko SLP 240 printer with a 175x Jet Direct print server	<u>Laser Printer:</u> HP LaserJet 2400 printer HP LaserJet 4200 printer HP LaserJet 4250 printer  <u>Label Printer:</u> Seiko SLP 240 printer with a 175x Jet Direct print server	Please verify your printers are HP-compatible and support the PCL printer language.  Please contact OMS Navigator software support for help in choosing proper printer drivers for different operating systems.  The 'N' and 'T' models of HP 2200, 4000, 4050, and 4100, 4200, and 4250 printers are acceptable.  It is not recommended that the user install the print drivers from the CD-ROM that ships with the Seiko SLP 240 printer.
<b>Palm Handheld Device</b>	HanDbase v3.0 software	Any Palm compatible device running Palm OS version 3.0, or the HP iPAQ Pocket PC running Windows CE operating system  HanDbase v3.0 software	Palm desktop software must be installed and configured by your hardware company.  It is highly recommended that a Palm device that includes a rechargeable cradle be purchased to reduce battery replacement costs.